

**In the Claims:**

This listing of claims will replace all prior versions, and listings, of claims in the application:

1. (Cancelled)
2. (Currently amended) A TV signal receiving tuner for receiving TV signals by dividing them into a plurality of frequency bands, comprising:
  - a local oscillator which oscillates at a frequency range corresponding to a received TV signal having a predetermined frequency band;
  - a second programmable divider which receives a local oscillation signal of the local oscillator and divides the local oscillation signal;
  - a second mixer which directly receives the local oscillation signal and which mixes the received TV signal and the local oscillation signal and frequency converts the received TV signal into an intermediate-frequency signal having a first frequency; and
  - a third mixer which receives an output of the second programmable divider and which mixes the received TV signal and an output of the second programmable divider and frequency converts the received TV signal into an intermediate-frequency signal having a second frequency,
  - wherein frequency conversion is carried out by the second mixer to receive a TV signal having a first frequency band, and
  - wherein frequency conversion is carried out by the third mixer to receive a TV signal having a frequency band lower than the first frequency band.
3. (Previously presented) The TV receiving tuner according to claim 2, wherein a dividing rate of the second programmable divider is variable and dependent upon a geographical location in which the TV receiving tuner is disposed.
- 4.-5. (Cancelled)

6. (Currently amended) A TV signal receiving tuner for receiving TV signals by dividing the TV signals into a plurality of frequency bands, comprising:  
a local oscillator which oscillates at a frequency range  
corresponding to a received TV signal having a predetermined frequency band;  
a first programmable divider which receives a local oscillation signal of the local oscillator and divides the local oscillation signal; and  
a first mixer which mixes the received TV signal and an output of the first programmable divider and frequency converts the received TV signal into an intermediate-frequency signal having a predetermined frequency;

~~The TV-receiving tuner according to claim 1, further comprising:~~

a first tracking filter to select the TV signal having the first frequency band;

a second tracking filter to select the TV signal having the second frequency band arranged in parallel to the first tracking filter; and

a PLL IC to output a tuning voltage that changes a frequency of the local oscillation signal output from the local oscillator[[]];

a low-noise first preamplifier having an automatic gain control (AGC) function provided after the first tracking filter; and

a low-noise second preamplifier having an AGC function provided after the second tracking filter,

wherein a dividing rate of the first programmable divider is variable and set to 1 to receive a TV signal having a first frequency band and to at most 1/2 to receive a TV signal having a second frequency band, the second frequency band being lower than the first frequency band, wherein the tuning voltage is applied to the first tracking filter and the second tracking filter to tune a pass band of one of the first tracking filter and the second tracking filter to a frequency of the TV signal to be received.

7. (Previously presented) The TV receiving tuner according to claim 6, further comprising:

a first image trap circuit to attenuate an image frequency signal corresponding to the TV signal to be received interposed between the first preamplifier and the second mixer; and

a second image trap circuit to attenuate the image frequency signal corresponding to the TV signal to be received interposed between the second preamplifier and the third mixer.

8.-11. (Cancelled)

12. (Previously presented) The TV receiving tuner according to claim 2, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and an output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 847 to 505 MHz, and a dividing rate of the second programmable divider is  $1/3$ , and wherein a dividing rate of the third programmable divider is  $1/5$ .

13. (Previously presented) The TV receiving tuner according to claim 2, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and an output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 803 to 473 MHz, and a dividing rate of the second

programmable divider is  $1/3$ , and wherein a dividing rate of the third programmable divider is  $1/9$ .

14. (Previously presented) The TV receiving tuner of claim 2, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and an output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 824 to 530 MHz, and a dividing rate of the second programmable divider is  $1/3$ , and wherein a dividing rate of the third programmable divider is  $1/4$ .

15. (Previously presented) The TV receiving tuner according to claim 2, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and an output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 767 to 473 MHz, and a dividing rate of the second programmable divider is  $1/3$ , and wherein a dividing rate of the third programmable divider is  $1/6$ .

16. (Previously presented) The TV receiving tuner according to claim 2, further comprising:

a first tracking filter to select the TV signal having the first frequency band;

a second tracking filter to select the TV signal having the second frequency band arranged in parallel to the first tracking filter; and  
a PLL IC to output a tuning voltage that changes a frequency of the local oscillation signal output from the local oscillator, and  
wherein the tuning voltage is applied to the first tracking filter and the second tracking filter to tune a pass band of one of the first tracking filter and the second tracking filter to a frequency of the TV signal to be received.

17. (Original) The TV receiving tuner according to claim 16, wherein the first tracking filter and the second tracking filter are a multi-tuning circuit.

18. (Previously presented) The TV receiving tuner according to claim 17, further comprising:

a low-noise first preamplifier having an automatic gain control (AGC) function provided after the first tracking filter; and  
a low-noise second preamplifier having an AGC function provided after the second tracking filter.

19. (Previously presented) The TV receiving tuner according to claim 18, further comprising:

a first image trap circuit to attenuate an image frequency signal corresponding to the TV signal to be received interposed between the first preamplifier and the second mixer; and  
a second image trap circuit to attenuate the image frequency signal corresponding to the TV signal to be received interposed between the second preamplifier and the third mixer.

20. (Previously presented) The TV receiving tuner according to claim 16, wherein the local oscillator outputs an oscillation signal having a frequency band of at least 847 to 505 MHz, and wherein the dividing rate of the first programmable divider may be set to different values including 1, 1/3 and 1/5.

21. (Previously presented) The TV receiving tuner according to claim 16, wherein the local oscillator outputs an oscillation signal having a frequency band of at least 803 to 473 MHz, and wherein the dividing rate of the first programmable divider may be set to different values including 1,  $1/3$  and  $1/9$ .

22. (Previously presented) The TV receiving tuner according to claim 16, wherein the local oscillator outputs an oscillation signal having a frequency band of at least 824 to 530 MHz, and wherein the dividing rate of the first programmable divider may be set to different values including 1,  $1/3$  and  $1/4$ .

23. (Previously presented) The TV receiving tuner according to claim 16, wherein the local oscillator outputs an oscillation signal having a frequency band of at least 767 to 473 MHz, and wherein the dividing rate of the first programmable divider may be set to different values including 1,  $1/3$  and  $1/6$ .

24. (Currently amended) The TV receiving tuner according to claim [[4]] 6, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and an output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 847 to 505 MHz, and a dividing rate of the second programmable divider is  $1/3$ , and wherein a dividing rate of the third programmable divider is  $1/5$ .

25. (Currently amended) The TV receiving tuner according to claim [[4]] 6, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and the output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 803 to 473 MHz, wherein a dividing rate of the second programmable divider is  $1/3$ , and a dividing rate of the third programmable divider is  $1/9$ .

26. (Currently amended) The TV receiving tuner according to claim [[4]] 6, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and the output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 824 to 530 MHz, wherein a dividing rate of the second programmable divider is  $1/3$ , and a dividing rate of the third programmable divider is  $1/4$ .

27. (Currently amended) The TV receiving tuner according to claim [[4]] 6, further comprising:

a third programmable divider to receive the oscillation signal of the local oscillator and divide the oscillation signal; and

a fourth mixer to mix the received TV signal and the output of the third programmable divider and frequency convert the received TV signal into an intermediate-frequency signal having a third frequency,

wherein the local oscillator outputs an oscillation signal having a frequency band of at least 767 to 473 MHz, wherein a dividing rate of the second programmable divider is  $1/3$ , and a dividing rate of the third programmable divider is  $1/6$ .